

EOS/ESD Protection Module for the DSA8300*1

80A02 Data Sheet



Features & Benefits

- Single-channel Electrostatic Discharge (ESD) and Electro-overstress (EOS) Damage Protection for Tektronix Electrical Sampling Modules
- Plugs into and is Powered from Sampling Mainframe
- Compatible with Tektronix Extender Cables
- <37 ps Reflected Rise Time when used with 80E04 or SD24 Electrical Sampling TDR Modules

Applications

- Electrical Sampling Module Input Protection for High-speed Electrical Signal Analysis
- Circuit-board Controlled Impedance Testing (TDR)

The **80A02 EOS/ESD Protection module** protects the sampling bridge of Tektronix electrical sampling module inputs from damage due to electro-overstress (EOS) and electrostatic discharge (ESD) from circuit boards and cables. The 80A02 is intended for use in applications such as electrical TDR circuit board testing and cable testing where large static charges can be stored in the DUT.

The 80A02 plugs into any available electrical sampling module plug-in slot of the DSA/TDS/CSA8K Series, legacy CSA11K Series, or legacy CSA803 Series sampling oscilloscopes.

The 80A02 provides a front-panel SMA connector for connecting the SMA test cable or probe signal from the DUT. The 80A02 passes the acquired DUT signal to a connected electrical sampling module input for measurement after an actuating control (from the matching P80318 or P8018 high-performance probe, or customer-provided external switch, TTL, or CMOS control logic input) which signals the 80A02 that the DUT has been grounded to discharge any electrostatic charge remaining in the DUT. When used with either matching P80318 or P8018 20 GHz handheld probe (with probe tip pressure actuating feature) the 80A02 provides a superior technique and performance capability for electrical sampling module EOS/ESD protection of acquired electrical signal and TDR measurement. (See P80318 or P8018 product description.)

*1 Also compatible with DSA8200, TDS/CSA8200, TDS/CSA8000B, and TDS/CSA8000 sampling oscilloscopes.

ASEAN / Australasia (65) 6356 3900

Austria 00800 2255 4835*

Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777

Belgium 00800 2255 4835*

Brazil +55 (11) 3759 7627

Canada 1 800 833 9200

Central East Europe and the Baltics +41 52 675 3777

Central Europe & Greece +41 52 675 3777

Denmark +45 80 88 1401

Finland +41 52 675 3777

France 00800 2255 4835*

Germany 00800 2255 4835*

Hong Kong 400 820 5835

India 000 800 650 1835

Italy 00800 2255 4835*

Japan 81 (3) 6714 3010

Luxembourg +41 52 675 3777

Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90

Middle East, Asia, and North Africa +41 52 675 3777

The Netherlands 00800 2255 4835*

Norway 800 16098

People's Republic of China 400 820 5835

Poland +41 52 675 3777

Portugal 80 08 12370

Republic of Korea 001 800 8255 2835

Russia & CIS +7 (495) 7484900

South Africa +41 52 675 3777

Spain 00800 2255 4835*

Sweden 00800 2255 4835*

Switzerland 00800 2255 4835*

Taiwan 886 (2) 2722 9622

United Kingdom & Ireland 00800 2255 4835*

USA 1 800 833 9200

* European toll-free number. If not accessible, call: +41 52 675 3777

Updated 10 February 2011

Characteristics

Characteristic	Description
Bandwidth	>25 GHz
Applicable Mainframes	DSA8300 Series, DSA8200 Series, TDS8000 Series, CSA8000 Series, CSA11800 Series, CSA803 Series
Connector Type	SMA female
Manual Control Input	Open circuit for DUT discharging standby state Closed circuit (<100 k Ω to ground) for measurement
Automated Control Input	Open circuit or logic low (<0.3 V) for DUT discharging Closed circuit or logic high (>1.0 V) for measurement
Control Signal Connector	Audio stereo phone mini-jack
Switching Time	20 ms (typical)

Ordering Information

80A02

EOS/ESD Protection Module, Single Channel.

Includes: User Manual, 1 – SMA 50 Ω termination cap, 1 – 12 in. length 20 GHz SMA cable.

Replaceable Items

Product	Description
015-1022-01	SMA 50 Ω termination
174-4878-xx	20 GHz SMA cable (12 in. length)

Accessories

Accessory	Description
174-5230-xx	SlotSaver Adapter Extender Cable. Brings power and control to the 80A02 when operated externally from the DSA/TDS/CSA mainframe, saving slot space (compatible with 80A06*2 and 80A02)

*2 Not compatible with DSA8300.



For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tektronix.com



Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

26 May 2011

85W-16656-4