

Power Analyzer Accessories



Tektronix provides a variety of accessories to use with our power analyzers to fit your application and measurement needs.

Fixed core Hall-effect transducers

Tektronix provides a variety of fixed core and split core current transducers matched to our power analyzers to fit your application and measurement needs. Fixed core transducers provide the highest accuracy available for both AC and DC current measurements, while the split core devices are ideally suited to making measurements in less accessible applications.

CT-xxxx-S Series



The CT-xxxx-S series offer the highest accuracy and linearity when uncompromised measurements are required. These transducers are sourced from LEM, a high-quality component company.

Features

- Very high accuracy (0.0054% - 0.0272%)
- Excellent linearity (3 ppm - 20 ppm)
- Extremely low temperature drift (0.5 ppm/k - 2.5 ppm/k)
- Wide frequency bandwidth (DC to 800 kHz)
- Closed loop (compensated) current transducer using an extremely accurate zero flux detector
- Electrostatic shield between primary and secondary circuit
- No insertion losses
- High immunity to external electrostatic and magnetic fields interference
- Low noise on output signal
- Tektronix custom cable assembly included for easy connection to the PA3000 power analyzer
- Compatible with standard PA3000 internal transducer supply (except CT-1000-S; order optional external power supply, Keithley models 2220 for two channels or 2231A for four channels)

Applications

- High power converters and inverters
- Motor drives
- Solar inverters
- UPS systems

CT-xxxx-M Series



The CT-xxxx-M series are designed for general purpose measurement applications where accuracy requirements are less stringent. These transducers are sourced from LEM, a high-quality component company.

Features

- Very good accuracy (0.4% - 0.5%)
- Very good linearity (<0.1%)
- Wide frequency bandwidth (DC to 150 kHz)
- Closed loop (compensated) current transducer using the Hall Effect
- Insulated plastic case recognized according to UL 94-V0.
- Low temperature drift
- Compatible with standard PA3000 internal transducer supply
- Tektronix custom cable assembly included for easy connection to PA3000
- No insertion losses
- High immunity to external interference

Applications

- High power converters and inverters
- Motor drives
- Solar inverters
- UPS systems

Current clamps



For quick connections in an environment where it is not possible to break the current path, a current clamp offers an easy way to measure AC current. The CL series current clamps are sourced from AEMC.

CL200

The CL200 is the latest in compact AC current probes. It is designed to provide quick connection to medium current circuits often found in industrial applications.

Features

- 0.5 A_{RMS} to 240 A_{RMS} measurement range
- 1000:1 transform ratio
- 40 Hz to 10 kHz response
- 1.0% to 3.0% accuracy, based on primary signal level
- Small, compact size
- Connects directly to Tektronix power analyzers
- Large jaw opening accommodates conductors up to 250 MCM
- Designed to EN61010, 600 V Cat. III safety standard

Applications

- High power converters and inverters
- Motor drives
- Solar inverters
- UPS systems

CL1200

The CL1200 is an AC current clamp designed for use in industrial and higher power environments. The ergonomic design allows it to easily clamp onto cables or small bus bars.

Features

- 100 mA_{RMS} to 1200 A_{RMS} measurement range
- 1000:1 transform ratio
- 30 Hz to 5 kHz response
- 0.5% to 1.5% accuracy, based on primary signal level
- Conforms to EN61010, 600 V Cat. III safety standard
- Low phase shift for power measurements

Applications

- High power converters and inverters
- Motor drives
- Solar inverters
- UPS systems

Measurement accessories

These accessories help to simplify your circuit connections and make your measurement tasks easier.

Test leads



PA-LEADSET Replacement lead set for Tektronix power analyzers. This insulated, stackable test lead set is rated for 1000 V, 32 A, CAT II, and is UL61010 compliant.

BB1000 Breakout Box

The BB1000 Breakout Box makes wiring connections between your device-under-test and Tektronix power analyzers easy and safe, by 'breaking out' the current flow for connection to the internal current shunt in the analyzer. It provides a line output socket to power your device under test (up to 10 A_{RMS}) and 4 mm sockets for direct connection to the Tektronix power analyzer terminals. The BB1000 Breakout box is offered in different versions with these receptacle styles:

- BB1000-UN: 120 V/240 V Universal receptacle
- BB1000-NA: 120 V North America receptacle
- BB1000-EU: 240 V Euro receptacle
- BB1000-UK: 240 V United Kingdom receptacle



BB1000-UN Breakout Box



BB1000-NA Breakout Box



BB1000-EU Breakout Box



BB1000-UK Breakout Box

Ballast-CT

The Tektronix Ballast-CT simplifies the measurement of output power and tube current in high frequency electronic lighting ballasts. This device is specifically designed for lighting applications, and overcomes problems that are usually found when using conventional or Hall Effect current transformers. When used in conjunction with a Tektronix PA1000 or PA3000 power analyzer, the free-standing Ballast-CT accessory provides a convenient and accurate solution to taking power measurements in lighting ballast circuits.



BALLAST-CT

- Convenience: No need to feed cables through a CT core
- High accuracy: Trifilar-wound toroidal design
- No cable positioning/contact error
- Wide bandwidth: High frequency design provides 5 kHz to 1 MHz bandwidth
- Wide current range: 5 mA to 1 A is compatible with many modern ballasts

Specifications

All specifications are guaranteed unless noted otherwise. All specifications apply to all models unless noted otherwise. The specifications are subject to change without notice.

CT-xxxx-S Series

Model	LEM part number	Nominal primary current (rms)	Nominal primary current (I_p , DC)	Nominal secondary current (I_s)	Supply voltage	Supply consumption	Transform ratio	Accuracy	Bandwidth
CT-60-S	IT 60-S	42 A	60 A	100 mA	± 15 V	80 mA + I_s	1:600	0.0272%	DC to 800 kHz
CT-200-S	IT 200-S	141 A	200 A	200 mA	± 15 V	80 mA + I_s	1:1000	0.0084%	DC to 500 kHz
CT-1000-S	IT 1000S/SP1	707 A	1000 A	1 A	± 15 V	80 mA + I_s	1:1000	0.0054%	DC to 500 kHz

Notes:

The CT-1000-S transducer requires a separate power supply. Tektronix recommends the Keithley model 2220 for two channels or 2231A for four channels.

The secondary current (I_s) = I_{measured} x the transform ratio.

CT-xxxx-M Series

Model	LEM part number	Nominal primary current (rms)	Nominal primary current (peak)	Nominal secondary current (rms)	Supply voltage	Supply consumption	Transform ratio	Accuracy	Bandwidth
CT-100-M	LF 205-S/SP3	100 A	200 A	100 mA	± 12 V to ± 15 V	17 mA + I_s	1:1000	$\pm 0.5\%$	DC to 100 kHz
CT-200-M	LF 205-S/SP1	200 A	420 A	100 mA	± 12 V to ± 15 V	17 mA + I_s	1:2000	$\pm 0.5\%$	DC to 100 kHz
CT-1000-M	LF 1005-S	1000 A	1500 A	200 mA	± 15 V to ± 24 V	28 mA + I_s	1:5000	$\pm 0.4\%$	DC to 150 kHz

CL Series

Model	AEMC part number	Measurement range	Transform ratio	Supply voltage	Accuracy	Bandwidth
CL200	MN213	0.5 A - 240 A _{RMS}	1000:1	Not needed	1.0% - 3.0%	40 Hz - 10 kHz
CL1200	SR604	100 mA - 1200 A _{RMS}	1000:1	Not needed	0.5% - 3.0%	30 Hz - 5 kHz

Ballast-CT

Operating current range 5 mA to 1 A_{RMS}

Operating frequency 5 kHz to 1 MHz

Accuracy

Amplitude Better than 1% (up to 500 kHz)

Phase Better than 1 degree (up to 500 kHz)

Maximum voltage, tube/ballast to output or Earth 600 V_{RMS}, CAT II

Isolation, tube/ballast to output 1 kVAC

Ordering Information

Models

CT-S Series	CT-60-S, CT-200-S, CT-1000-S
CT-M Series	CT-100-M, CT-200-M, CT-1000-M
CL Series	CL200, CL1200
Test Leads	PA-LEADSET
Breakout Box	BB1000-UN, BB1000-NA, BB1000-EU, BB1000-UK
Ballast-CT	BALLAST-CT

Accessories

All CT series current transducers (except for CT-1000-S) include cabling that allows easy and direct connection to the ± 15 V supply on the PA3000 Power Analyzer, and directly to the 1 A shunt.

The CT-1000-S transducer requires a separate power supply. Tektronix recommends the Keithley model 2220 for two channels or 2231A for four channels, which can supply power for up to two CT-1000-S current transducers.

Warranty

All parts warranted for 1 year.



Tektronix is registered to ISO 9001 and ISO 14001 by SRI Quality System Registrar.

ASEAN / Australasia (65) 6356 3900
Belgium 00800 2255 4835*
Central East Europe and the Baltics +41 52 675 3777
Finland +41 52 675 3777
Hong Kong 400 820 5835
Japan 81 (3) 6714 3010
Middle East, Asia, and North Africa +41 52 675 3777
People's Republic of China 400 820 5835
Republic of Korea +822 6917 5084, 822 6917 5080
Spain 00800 2255 4835*
Taiwan 886 (2) 2656 6688

Austria 00800 2255 4835*
Brazil +55 (11) 3759 7627
Central Europe & Greece +41 52 675 3777
France 00800 2255 4835*
India 000 800 650 1835
Luxembourg +41 52 675 3777
The Netherlands 00800 2255 4835*
Poland +41 52 675 3777
Russia & CIS +7 (495) 6647564
Sweden 00800 2255 4835*
United Kingdom & Ireland 00800 2255 4835*

Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
Canada 1 800 833 9200
Denmark +45 80 88 1401
Germany 00800 2255 4835*
Italy 00800 2255 4835*
Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90
Norway 800 16098
Portugal 80 08 12370
South Africa +41 52 675 3777
Switzerland 00800 2255 4835*
USA 1 800 833 9200

* European toll-free number. If not accessible, call: +41 52 675 3777

For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tek.com.

Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.



14 Mar 2016 55W-30309-0

